



WMP030/811 con motore brushless CC

WMP030/811 with brushless DC motor

WMP 030/811	BL070.240 / BL070.480 / BL070.48B						
	24V / 48V						
ir	n ₂ MIN			n ₂ MAX			n ₁ MAX [rpm]
		M ₂	sf		M ₂	sf	
67.5	4.4	29	2.8	44.4	32	2.5	3000
101.3	3.0	39	2.1	29.6	47	1.7	
135.0	2.2	49	1.6	22.2	59	1.3	
202.5	1.5	59	1.3	14.8	76	1.1	
270.0	1.1	65	1.2	11.1	80	1.0*	
337.5	0.9	76	1.1	8.9	80	1.0*	
405.0	0.7	80	1.0*	7.4	80	1.0*	

Nota: I valori * indicano il superamento della coppia massima sopportata dal riduttore per il servizio in S1.

*N.B.: value * indicate that maximum torque withstood by gear reducer for service in S1 is exceeded.*

Tipo Type	Numero di poli Number of poles	Numero di fasi Number of phase	Tensione Rated voltage [V]	Numero di giri Rated speed [rpm]	Coppia nominale Rated torque [Nm]	Potenza nominale Rated power [W]
BL070.240	8	3	24	3000	0.7	220
BL070.480 BL070.48B	8	3	48	3000	0.7	220
Tipo Type	Coppia massima Peak torque [Nm]	Corrente nominale Rated current [A]	Resistenza Resistance [ohm]	Induttanza Inductance [mH]	Corrente massima Peak current [A]	Peso Weight [kg]
BL070.240	2.1	13	0.091	0.23	26	2.1
BL070.480 BL070.48B	1.4	6.5	0.34	1.0	13	2.1



WMP030/811..U
+
BL070.240
BL070.480

